



Camtraptions PIR v4 Manual (*extract*)



Set Off Time

The **Window Off Time** setting defines the time of day when the sensor becomes **inactive**, marking the end of the period during which motion detection and triggering are enabled.

This setting works together with the **Window On Time** to establish the daily operating period for the sensor. For example, if you want the sensor to operate **only at night**, you might set the *Window On Time* to **18:00 (6:00 p.m.)** and the *Window Off Time* to **06:00 (6:00 a.m.)**.



Setting the Window Off Time

1. From the **Home Screen**, press the **Right Arrow** until you reach the **Window Off Time** screen.
2. Use the **Up** or **Down** buttons to adjust the **hour** value.
3. Press the **Set** button to confirm the hour.
4. The **minute** value will then begin flashing — use the **Up** or **Down** buttons to adjust it.
5. Press **Set** again to save the time.

The time is entered in **24-hour format** (00:00 to 23:59).

Notes

- Ensure the **Time Windows** feature is **enabled** for this setting to take effect.
- The **sensor will remain inactive** outside the defined time window.
- If the Off Time is set to the same value as the On Time, the sensor will remain active at all times.

- For reliable operation, confirm that the **sensor clock** is set correctly before defining time windows (see [Set Clock Time](#) section).
-

This manual extract applies to firmware version 1.19.

Exported from docs.camtraptions.com.