



Camtraptions PIR v4 Manual (*extract*)



Set On Time

The **Window On Time** setting defines the time of day when the sensor becomes **active** — in other words, the start of the period during which motion detection and triggering are enabled.

This feature works in conjunction with the **Time Windows** setting. For example, if you wish the sensor to operate **only at night**, you might set the *Window On Time* to **18:00 (6:00 p.m.)** and the *Window Off Time* to **06:00 (6:00 a.m.)**.



Setting the Window On Time

1. From the **Home Screen**, press the **Right Arrow** until you reach the **Window On Time** screen.
2. Use the **Up** or **Down** buttons to adjust the **hour** value.
3. Press the **Set** button to confirm the hour.
4. The **minute** value will then begin flashing — use the **Up** or **Down** buttons to adjust it.
5. Press **Set** again to save the time.

The time is entered in **24-hour format** (00:00 to 23:59).

Notes

- Ensure the **Time Windows** feature is **enabled** for this setting to take effect.
- For reliable operation, confirm that the **sensor clock** is set accurately before adjusting time windows (see [Set Clock Time](#) section).

This manual extract applies to firmware version 1.19.

Exported from docs.camtraptions.com.